

EXIDE
INDUSTRIAL

 **EXIDE**
500+
INVARED

The Red Tubular



अब 20% Zyada Electrolyte

Mera Inverter Maange Only **INVA**

Presenting **INVARED 500+**, the next generation tubular battery designed specially to withstand long and frequent powercuts and requiring very low maintenance.

FEATURES

- More than 20% extra electrolyte which means lesser topping-up frequency and better thermal management
- Tubular Technology
- Minimum maintenance
- Electrolyte level indicator
- Suited for frequent and long powercuts
- Deep cycle design (600 – 700 cycles at 80% D.O.D.)
- Abuse resistant
- Faster recharge
- Operating sp.gr. 1.250 ± 0.005 at 27°C

TECHNICAL SPECIFICATION

Model	Capacity*	Dimension (+/-3mm)			Weight (Kg +/-5%)		Volume of Electrolyte (1.220 Sp. Gr) Liters/Cell	Initial charge Minimum AH input (AH)	Initial Charge at Constant Current (A)		Constant Potential Limiting Current (Amps)	Trickle Charge (Current in mA)	
		Length	Width	Height*	Dry	Filled			Start (upto 2.36 vpc)	Finish (upto 2.75 vpc)		Min.	Max.
INVARED 500+	150 Ah	506	220	273	34.90	52.50	2.40	585	15.60	7.80	26	130	520

*The height mentioned is upto terminal top. *At 27°C when discharged at C20 upto 1.75 vpc (1.280 sp. gr)

HIGHER DISCHARGE RATES (OPTIONAL)

Hours	Capacity Ah	INVARED 500+	10	5	3	1
Capacity Ah	INVARED 500+	130	108	93	65	

INITIAL CHARGING INSTRUCTIONS

1. Filling in Specific Gravity 1.220 +/- 0.005 at 27°C	5. Conditions of fully charged	a) 3 consecutive hourly readings of specific gravity and voltage become constant
2. Rest Period 4 - 6 hrs.		b) Top of charge voltage will be around 16.2V – 16.5V
3. Minimum Ah input 585Ah for INVARED 500+		c) All cells should gas freely
4. In order to reduce the charging time, the following routine may be adopted. For IR500+, the initial charging current may be 15.6A upto 2.36vpc, followed by 7.8A upto 2.75vpc. However, in both cases, minimum Ah input to be given. Under no circumstances, battery temperature should exceed 50°C. In case the temperature exceeds 50°C, adequate rest to be given till the electrolyte temp. comes to ambient temp. and charging to be continued.		d) Minimum Ah has been given
	6. Specific Gravity at fully charged condition	1.250 +/- 0.005 at 27°C

NORMAL RECHARGING INSTRUCTIONS

Recharging through Inverter at constant potential mode of 14.4V with limited current as specified. After battery potential reaches 14.4V, the battery should continue in float charge mode at constant potential of 13.8V.

BATTERY SELECTION CHART

Inverter Rating VA	DC input voltage	Back-Up Duration					
		6 Hrs.	5 Hrs.	4 Hrs.	3 Hrs.	2 Hrs.	1 Hr.
300	12	IR500+	IR500+	IR500+	IR500+	IR500+	IR500+
500	12	2P IR500+	2P IR500+	2P IR500+	2P IR500+	2P IR500+	2P IR500+
	24	2S IR500+	2S IR500+	2S IR500+	2S IR500+	2S IR500+	2S IR500+
700	12	3P IR500+	2P IR500+	2P IR500+	2P IR500+	2P IR500+	2P IR500+
	24	2P X 2S IR500+	2S IR500+	2S IR500+	2S IR500+	2S IR500+	2S IR500+
1000	12	4P IR500+	3P IR500+	3P IR500+	2P IR500+	2P IR500+	2P IR500+
	24	2P X 2S IR500+	2P X 2S IR500+	2P X 2S IR500+	2S IR500+	2S IR500+	2S IR500+
1300	24	2S X 3P IR500+	2S X 2P IR500+	2S X 2P IR500+	2S X 2P IR500+	2S IR500+	2S IR500+
	48	4S X 2P IR500+	4S IR500+	4S IR500+	4S IR500+	4S IR500+	4S IR500+
2000	24	2S X 4P IR500+	2S X 3P IR500+	2S X 3P IR500+	2S X 2P IR500+	2S X 2P IR500+	2S IR500+
	48	4S X 2P IR500+	4S X 2P IR500+	4S X 2P IR500+	4S IR500+	4S IR500+	4S IR500+

S= Series connection; P= Parallel connection. 4S X 2P IR500+ means a string with 4 nos IR500+ in series and 2 nos such string in parallel. IR500+ means INVARED 500+.

Statutory Notice:

All batteries contain lead, which is harmful for humans and environment. As per statutory requirements, the used battery must be returned to the authorized dealer, manufacturer or at the designated collection centres.

Contact our Exide Powercentre Showrooms for Sales & Services



INVARED is a product of ISO 9001 and ISO 14001 certified factories

Head Office Kolkata "Exide House", 59E Chowringhee Road, Kolkata - 700 020, Phone (033) 2283 2120/33/36/50/51/71/ 2238/39, Fax (033) 2283 2632/37	Kolkata 6A Hatibagan Road, Entally, Kolkata - 700 014, Phone (033) 2284 3137, 2286 1860/6193 Fax (033) 2289 7455	Lucknow Phone (0522) 223 1255, 262 0722/6971, 261 5280, Fax (0522) 261 8089
Corporate Marketing Office Kolkata 6A Hatibagan Road, Entally, Kolkata - 700 014, Phone (033) 2286 6158/6159, Fax (033) 2286 6186 E-mail: indicore@ent.exide.co.in	Branch Offices Bhubaneswar Phone (0674) 243 1385/1847, Fax (0674) 243 1385	Varanasi Phone (0542) 250 1680, Fax (0542) 250 1296 RP
Regional Offices New Delhi "Exide House", 3E/1 Link Road, Jhandewalan Extension, New Delhi - 110 055, Phone (011) 2362 7095/ 96/98, 5154 0626, Fax (011) 2355 5703	Guwahati Phone (0361) 234 2500/1119	Bangalore Phone (080) 5128 3492-5/2357 8672, Fax (080) 559 9624
Chennai 21/22, Alandur Road, Guindy, Chennai - 600 032, Phone (044) 2234 7326, 2231 6725 (Direct)/26, Fax (044) 2231 1216	Jamshedpur Phone (0657) 242 6847/8349	Coimbatore Phone (0422) 222 1846, Fax (0422) 222 1737
Mumbai "RAHEJAS", 5th Floor, BC Main Avenue, V P Road, Santacruz (West), Mumbai - 400 054, Phone (022) 2646 5283/84, Fax (022) 2646 5042	Patna Phone (0612) 222 6632, 221 1040, 257 3039, Fax (0612) 223 1569	Hyderabad Phone (040) 5516 3958 (D), 5569 6633
	Siliguri Phone (0353) 254 0321	Kochi Phone (0484) 240 9128 (D), Fax (0484) 253 7869
	Chandigarh Phone (0172) 500 0014, 265 7409/4387/4553, Fax (0172) 265 4395	Ahmedabad Phone (079) 2685 6697 (D)/8/9661, Fax (079) 2685 6698
	Ghaziabad Phone (0575) 273 4574, 283 2172/73	Indore Phone (0331) 255 6290/91, Fax (0331) 249 3395
	Jaipur Phone (0141) 229 3704/3799, Fax (0141) 229 2877	Mumbai Phone (022) 2646 5041, Fax (022) 2646 5042
	Jalandhar Phone (0181) 553 4983, 223 7870, 223 7874, Fax (0181) 245 9571	Nagpur Phone (0712) 259 4722, 561 5882/83, Fax (0712) 259 1479
		Pune Phone (020) 3230 4043 (D)/41/42, Fax (020) 2422 3843
		Vadodara Telefax (0265) 235 4240

This catalogue is issued to provide outline information only and is not deemed to form part of an offer or contract. Our policy is one of continued improvement and we reserve the right to change details without prior notice.

PHX/IR/10K/08-2006

*Applied for

www.exideindustries.com